

Additional Installation Instructions for: Vertex Continuous

1

Mains leads can be brought down into any luminaire

Use cable tie to fix mains lead to suspension wire

Cut off any excess suspension wire

Fixing suspension wires

a Fix ceiling boss to mounting surface using suitable wood screw

b Feed wire into body as shown - screw body into ceiling boss

c Thread wire into clutch body higher than required to enable easy downward adjustment.

d Offer housing up to 'Y' section wire and feed ends into keyhole slots, slide across to small end to secure.

Adjust height of housing downwards by pressing top of clutch.

2 Wiring

LUMINAIRES MUST BE EARTHED

L1 - Unswitched Live (Red)
L - Live (Brown)
⊕ - Earth (Green/Yellow)
N - Neutral (Blue)

3

Fix adjacent suspension wires in position

Connect luminaires by locating plug and socket together then laterally slide the two luminaires together

Adjust height of housing downwards by pressing top of clutch.

Fixing Centres (mm)	
600mm	600
1200mm	1155
1500mm	1444
$d = 34.0\text{mm}$	

Cooper Lighting and Safety Ltd
Wheatley Hall Road, Doncaster, South Yorkshire, DN2 4NB

Sales	General	Major Projects London	International Sales
T: +44 (0)1302 303303	+44 (0)1302 321541	+44 (0)1992 787999	+44 (0)1302 303250
F: +44 (0)1302 367155	+44 (0)1302 303220	+44(0)1992 787222	+44 (0)1302 303251
E: sales@cooper-ls.com	technical@cooper-ls.com	london@cooper-ls.com	export@cooper-ls.com

Additional Installation Instructions for: Vertex Continuous

1

Mains leads can be brought down into any luminaire

Use cable tie to fix mains lead to suspension wire

Cut off any excess suspension wire

Fixing suspension wires

a Fix ceiling boss to mounting surface using suitable wood screw

b Feed wire into body as shown - screw body into ceiling boss

c Thread wire into clutch body higher than required to enable easy downward adjustment.

d Offer housing up to 'Y' section wire and feed ends into keyhole slots, slide across to small end to secure.

Adjust height of housing downwards by pressing top of clutch.

2 Wiring

LUMINAIRES MUST BE EARTHED

L1 - Unswitched Live (Red)
L - Live (Brown)
⊕ - Earth (Green/Yellow)
N - Neutral (Blue)

3

Fix adjacent suspension wires in position

Connect luminaires by locating plug and socket together then laterally slide the two luminaires together

Adjust height of housing downwards by pressing top of clutch.

Fixing Centres (mm)	
600mm	600
1200mm	1155
1500mm	1444
$d = 34.0\text{mm}$	

Cooper Lighting and Safety Ltd
Wheatley Hall Road, Doncaster, South Yorkshire, DN2 4NB

Sales	General	Major Projects London	International Sales
T: +44 (0)1302 303303	+44 (0)1302 321541	+44 (0)1992 787999	+44 (0)1302 303250
F: +44 (0)1302 367155	+44 (0)1302 303220	+44(0)1992 787222	+44 (0)1302 303251
E: sales@cooper-ls.com	technical@cooper-ls.com	london@cooper-ls.com	export@cooper-ls.com